

REM1

Remote Control with Backlit Buttons



Description

The REM1 is a water-resistant, four-button remote control and is available in either a 433MHZ or 868Mhz version.

The REM1 is constructed with solid, stylish clear blue plastic, with a red backlight behind the buttons.

Features

- Four backlit buttons
- Performs up to 5 different actions
- Water resistant
- Available in 433Mhx or 868Mhz
- Easily replaceable battery
- Typical wireless range from 30m-60m

REM1 Overview



Water Resistant

The REM1's water resistant casing ensures that the REM1 is protected against accidental splashes or rain.

Replaceable battery

Simply remove the screws and the back cover and replace with a new 3V lithium battery (CR2032).

Backlit Buttons

All buttons are backlit so are easily seen in the dark, and the remote also features a red LED near the top so that it is easy to tell that the button push has been transmitted.

Compatibility

Consoles/Control Panels

- Magellan All-In-One Wireless Console (MG6130 / MG6160, MG-6030 / MG-6060)
- 32-Zones Wireless Transceiver Control Panel (MG5000 / MG5050)
- Spectra 1759MG control panel

Wireless Expansion Modules

- Magellan Wireless Expansion Module (RTX3)
- Wireless Receiver (RX1)

Specifications

Battery	One 3V lithium battery (CR2032)
Range	23m with the RX1
	30m with the all-in-one consoles
	45m with the MG5000 and MG5050
	60m with the RTX3 and 1759MG